

General Information

1993

Covers Models:
Toshiba 1400 TB5
CRT: A34JLL90X49
Remote Control:
23120092 (CT-9616)
Main Power Button:
23443463

Matrix

Item	See Model
Service Adjustments	Toshiba 1400 RBT 91/92 Book.
Trouble Shooting Guides	Toshiba 1400 RBT 91/92 Book.


Specifications

Input Power Rating	53 W, AC240V, 50Hz
Aerial Input Impedence	75 ohm unbalanced type for UHF
Receiving Channels	
PAL-I Standard	UHF 21 - 68
Intermediate Frequencies:	
Picture IF	39.5 MHz
Sound IF	33.5 MHz
Picture Tube	A34JLL90X49 (34cm)
Sound Output	1W (at 10% harmonic distortion)
Speakers	77mm round

Recommended Safety Parts

Item	Part No.	Description
C440	24095892	PF, 6800pF, $\pm 3\%$, 1600V
C463	24212222	CD, 2200pF, $\pm 10\%$
F801	23144896	Fuse, T2.0A
F803	23144876	Fuse, 0.5A
L462	23227257	Deflection Yoke, ODY-M1449
L901	23200781	Coil, Degaussing, TSB-2229
P801	23171814	Power Cord
Q404	A6868673	Transistor, 2SD1426(FA, E)
R361	24383271	OMF, 270 ohm, 2W
R416	24007566	Cement, 2k ohm, 5W
R801	24007848	Cement, 6.2 ohm, 5W
R816	24531100	FR, 10 ohm, 1/2W
R847	24007622	Cement, 5100 ohm, 5W
R890	24000918	PTC Thermistor, 18 ohm, $\pm 20\%$, 290V
R920	24000890	FR, 1.6 ohm, 1W
RA60	24007405	Cement, 3900 ohm, 10W
RF80	24531100	FR, 10 ohm, 1/2W
RF81	24383103	OMF, 10k ohm, 2W
RF82	24556109	FR, 1 ohm, $\pm 10\%$, 1/2W
RF83	24531100	FR, 10 ohm, 1/2W
RF85	24556109	FR, 1 ohm, $\pm 10\%$, 1/2W
S801	23145434	Switch, Power, 2C2P
T401	23224983	Transformer, Horiz. Drive, TLN1039
T461	23236264	Transformer, Flyback, TFB4104AD
T801	23211929	Line Filter, TRF3130
T802	23217078	Transformer, Converter, TPW3185
V901	23312387	Picture Tube, A34JLL90X
V901A	23902022	Socket, CRT, 8P

CRT Diagram



U902A MAIN BOARD PS3826-1

